



MX120

MIXER AMPLIFIER WITH BT, 120W [100V]



- 100V Line Output
- USB Player
- Remote Control
- Extended Compatibility
- RCA Input
- Microphone Input

The MX120 is a 120W (100V) amplifier with an ultra-small size and lightweight for incorporating into your small to medium-sized installations allowing its installation where you want, and can be installed in any place keeping the installation design. With MX120, you can have multiple audio signal solutions USB, RCA, XLR, AUX and BT. This amplifier incorporates a multimedia player that allows you to control and reproduce the USB.

<p>Product Type Mixer Amplifier with BT</p>	<p>Frequency Response (-6dB) 80Hz - 16kHz</p>	<p>Amplifier Technology D Class Amplifier</p>
<p>Amplifier Power 120W</p>	<p>Speaker Output 100V</p>	<p>THD+N <0.5%</p>
<p>SNR (Signal to Noise Ratio) Mic: >74dB Line-in: >80dB</p>	<p>Input Sensitivity Mic: 60mV (±15mV) Line-in: 300mV(±20mV)</p>	<p>Mixer 3 Channels</p>
<p>Wireless Connection System BT v5.0</p>	<p>Wireless Range 10m (32.8ft)</p>	<p>Audio Signal Inputs BT Microphone CD Player USB</p>
<p>Input Connectors 1 x Stereo RCA 1 x MIC (TS) 1 x MIC or AUX (XLR) 1 x Line-in (Phoenix Connector) 1 x 100V IN (Phoenix Connector) 1 x USB A Type</p>	<p>Audio Signal Outputs Line Audio</p>	<p>Output Connectors 1 x Stereo RCA</p>
<p>Protections DC Voltage Overload Short-Circuit</p>	<p>Cooling Type Speed Controlled Fan</p>	<p>Power Input AC 180V - 250V / 50Hz - 60Hz and/or DC 24V - 6A</p>
<p>Power Consumption 150W</p>	<p>Special Features Ducking Priority Mic. Phantom Power (+48V) Bass Adjust.: ±10dB (100Hz) Treble Adjust.: ±10dB (10kHz)</p>	<p>Construction Aluminum / Steel</p>
<p>IP Rating Indoor Use</p>	<p>Dimensions (WxHxD) 200 x 44 x 190mm (7.9" x 1.7" x 7.5")</p>	<p>Net Weight 1.5kg (3.3lb)</p>
<p>Shipping Weight 2kg (4.4lb)</p>		