



## MX350

6-ZONE MIXER AMPLIFIER, 350W  
[100V|8Ω]



-  Speaker Zone Output
-  FM Radio Function
-  USB Player
-  Extended Compatibility
-  Remote Control
-  Microphone Input

The MX350 is a 6-Zone Mixer Amplifier, 350W [100V|8Ω] for your medium to big size installations, You can operate your MX350 @ 4-16Ω or 70V/100V and install it according your needs. With MX350, you can have multiple audio signal solutions USB, Microphone, SD card and radio. This amplifier incorporates a multimedia player that allows you to control and reproduce the USB and SD card.

### Product Type

Multi-Zone Mixer Amplifier

### Frequency Response (-6dB)

80Hz - 16kHz

### Amplifier Technology

AB Class Amplifier

### Amplifier Power

350W

### Speaker Output

100V | 4Ω - 16Ω

### Zones Output

6 Zones

### THD+N

<1%

### SNR (Signal to Noise Ratio)

Mic: >71dB | Line-in: >85dB

### Input Sensitivity

Mic: 3mV (±0.5mV) | Line-in :  
300mV(±50mV)

### Mixer

7 Channels

### Audio Signal Inputs

Microphone | CD Player | USB | SD Card  
| FM Radio | BT

### Input Connectors

3 x Stereo RCA | 4 x MIC (TS) | USB | SD  
Card Slot | FM Antenna (75Ω)

### Audio Signal Outputs

Line Audio

### Output Connectors

1 x Stereo RCA

### Speakers Output Connectors

Low Impedance: Binding Posts | 100V:  
Screw Connector

### Protections

DC Voltage | Overload | Short-Circuit

### Cooling Type

Speed Controlled Fan

### Power Input

AC 220V - 240V / 50Hz - 60Hz

### Power Consumption

650W (3A)

### Special Features

Chime | Ducking | Priority Microphone |  
Bass Adjust.: ±10dB (100Hz) | Treble  
Adjust.: ±10dB (10kHz)

### Fittings

2U 19" Rack

### Handles

Two on Front

### Construction

Aluminum / Steel

### IP Rating

Indoor Use

### Dimensions (WxHxD)

483 x 88 x 338mm (19" x 3.5" x 13.3")

### Net Weight

16kg (35.3lb)

### Shipping Weight

17kg (37.5lb)