



M1

DIGITAL STEREO MIXER

-  Extended Compatibility
-  Audio Streaming
-  Effects
-  Microphone Input
-  USB Player
-  USB Powered

The M1 is an ultra compact and lightweight 4-channel digital stereo mixer with BT to use as a “traditional mixer” or USB Audio Interface. When used as a USB Audio Interface, it can be connected to a PC, allowing the production of online content with high-fidelity sound, either for real-time transmission (streaming) or production of offline videos and podcasts. You can also record directly to a USB stick.

Product Type

Digital Mixing Console (USB Audio Interface)

Mixer

4 Channels (2 x Mono | 1 x Stereo)

DSP Technology

24bit | 192kHz

Effects

Ambience, Bathroom, Room, Plate, Spring, Hall, Warehouse, Cathedral, Gated Reverb, Chorus, Chorus Reverb, Phaser, Phaser Reverb, Flanger, Flanger Reverb, Rotary, Delay

Wireless Connection System

BT v5.0

Wireless Range

10m (32.8ft)

Audio Signal Inputs

BT | Microphone (+48V) | Instrument (HI-Z) | USB | AUX | CD Player | PC (2 Channels)

Input Connectors

2 x XLR / TRS combo | 1 x 3.5mm Stereo Jack | 1 x USB | 1 x Stereo RCA | 1 x USB 2.0

Audio Signal Outputs

Main Output | Headphones | PC (2 Channels)

Output Connectors

2 x Balanced TRS | 1 x 3.5mm Stereo Jack | 1 x USB 2.0

Power Input

Power Supply: AC 100V - 240V 50Hz/60Hz | DC 5V - 2A

Power Consumption

10W (2A)

Special Features

HI-Z, Low Cut, EQ (LOW, MID, HIGH), Phantom Power (+48V), Effects, USB Stick Recording, PC Recording

Construction

Reinforced Plastic

Dimensions (WxHxD)

153 x 64 x 175mm (6 x 2.5 x 6.9 in)

Net Weight

0.6kg (1.3lb)

Shipping Weight

0.9kg (2lb)