



A40

STEREO AMPLIFIER WITH BT, 60W

- 8Ω Minimum Impedance
- Extended Compatibility
- Space Saving
- Discreet Design
- AUX Input
- Ultra-Thin Design

The A40 is a 60W amplifier with an ultra small size and weight to integrate in your small and medium installations allowing you to install it where it is most convenient for you. It can be installed on a wall, ceiling or furniture for space saving keeping the space decor. Take advantage of the BT connection, sonorizing your space easily. You can use your A40 down to 8Ω minimum impedance.

Product Type

BT Class D Amplifier

Frequency Response (-6dB)

20Hz - 20kHz

Amplifier Technology

Class D Amplifier

Amplifier Power

2 x 30W@8Ω

Speaker Output

8Ω - 16Ω

THD+N

<0.1%

SNR (Signal to Noise Ratio)

>82dB

Input Sensitivity

0dBV (0.7V)

Wireless Connection System

BT v2.1 + EDR

Wireless Range

10m (32.8ft)

Audio Signal Inputs

BT | Stereo Line-in

Input Connectors

3.5mm Stereo Jack

Cooling Type

Convection

Power Input

AC 100V-240V / 50Hz-60Hz

Power Consumption

0.24W - Idle

Construction

Aluminum

IP Rating

Indoor Use

Dimensions (WxHxD)

100 x 35 x 125mm (3.9" x 1.4" x 4.9")

Fixation

Screw Fixation to Wall / Ceiling

Net Weight

330g (0.731lb)

Shipping Weight

350g (0.771lb)