



dm20m

20-CHANNELS DIGITAL MIXER



Product Description

It has two USB interfaces for recording, playback, scene memory, WIFI connection. 20 inputs including 12 pro mic and 2 stereo, professional digital signal input port, 8 BUSSES including 8 assignable analog and digital output ports.

Furthermore, a 7" Android-powered HD touch screen for WIFI wireless control and nine 100mm electric faders are used to adjust parameters for intuitive operation.

This is a full-function compact digital mixer from Soundking that features premium hardware, touch operation, iPad remote control, the 4th generation SHARC floating point processor, 24bit/192kHz, AD/DA conversion, 8 effect modules, reverb, delay, modulation, GEQ.



Feature

- 8 buses
- 2 USB ports
- Scene memory
- 7" Touch screen
- iPad remote control
- Fourth-generation 40-bit SHARC processor
- DSP with built-in 8 effects, REVERB, DELAY, GEQ, etc.

Application: Recording studio, Live performance, Conference hall, Pub, TV station, Band, etc.

Supports control via Wi-Fi.

with the application on iPad



DM20 remote App



Specifications

| | | | |
|--------------------------------------|---------------------------|-------------------------------------|---------------|
| Model: | DM 20M | Type: | DIGITAL MIXER |
| Number of Interface Input: | 20 | BUS: | 8 |
| DSP: | YES | Gain: | YES |
| Multitrack-Recording: | NO | USB/SD Direct Recording: | YES |
| USB Play: | YES | Bluetooth Play: | NO |
| Remote Control: | YES | Touch Screen: | YES |
| Number of Mono Ins: | 12 | Number of Stereo Ins: | 2 |
| MIC IN Interface: | XLR-1/4" (x8), Combo (x4) | LINE IN Interface: | 4 x TRS |
| Output Interface: | XLR (x10) | Number of Stereo S/PDIF Connectors: | 1 |
| Number of Stereo AES/EBU Connectors: | 1 | Number of Headphone Connectors: | 1 |
| Phantom Power: | 48V | 19" Rackmount: | YES |
| Height in mm: | 100 mm | Width in mm: | 325 mm |
| Depth in mm: | 445 mm | Weight in kg: | 5.3 kg |